

## Direct Link Networks (II)

Assigned reading: Peterson and Davie: Chapter 2.5 – 2.9. All problems carry equal weight. Please show all your work.

### 1. Multiple Access

Nodes A and B are attached via a 200 m cable. Signal propagation speed is  $2 \times 10^8$  m/sec, and the transmission rate is 40 Mbps. There is a single repeater between A and B, inserting a 10-bit delay. A has a frame of 175 bytes (including all headers and preambles) to send to B at  $t=0$ .

- What is the one-way propagation delay between A and B?
- Find the time when A's packet is delivered at B.

In addition to A's frame, B also has a frame of 175 bytes to send to A. CSMA/CD with backoff intervals of multiples of 512 bits is used. When a collision occurs, A chooses  $K=0$  and B chooses  $K=1$  in the exponential backoff protocol. Ignore the jam signal and assume frame is sent immediately on an idle line. When will B's frame be delivered at A in the following two instances?

- B is ready to send at  $t=1 \mu\text{s}$ . Is the line busy? Is a collision detected? When will B's frame arrive at A?
- B is ready to send at  $t=50 \mu\text{s}$ . Is the line busy? Is a collision detected? When will B's frame arrive at A?

### 2. Ethernet Timing

This problem is about the Ethernet/IEEE 802.11 access protocol. To be definite, suppose that if a host detects a transmission while it is transmitting a frame, then: (i) if the host has already transmitted the 64 bit preamble, the host stops transmitting the frame and sends a 32 bit jamming sequence; (ii) else the host finishes transmitting the 64 bit preamble and then sends a 32 bit jamming sequence. For simplicity, assume a collision is detected as soon as an interfering signal first begins to reach a host. Suppose the packets are 512 bits long, which is the minimum length allowed. Hosts A and B are the only active hosts on a 20 Mbps Ethernet and the propagation time between them is  $6 \mu\text{s}$ , or 120 bit durations. Suppose A begins transmitting a frame at time  $t = 0$ , and just before the beginning of the frame reaches B, B begins sending a frame, and then almost immediately B detects a collision.

- Does A finish transmitting the frame before it detects that there was a collision? Explain.
- What time does A finish sending a jamming signal? What time does B finish sending a jamming signal?
- What time does A first hear an idle channel again? What time does B first hear an idle channel again?
- Suppose each host next decides to retransmit immediately after hearing the channel idle. After the resulting (second) collision: When does A next hear the channel idle? When does B next hear the channel idle?
- Suppose after the second collision, A decides to wait 512 bit durations to retransmit (if it hears silence after that long) and B decides to retransmit immediately after hearing a silent channel. Is the transmission of host B successful?
- At the time A was planning to send its second retransmission, it senses a carrier present. Suppose at that particular time A decides to wait  $3 \times 51.2 \mu\text{s}$  more until its next retransmission. What time does host A finish sending its packet?

### 3. Ethernet

Consider the following two possibilities:

- We put 20 hosts on an Ethernet operating at 10 Mbps.
- We create two separate Ethernets, with 10 hosts operating on each of the Ethernets, and each of the Ethernets operating at 5 Mbps.
  - Suggest one potential advantage of approach (i) compared to (ii).
  - Suggest one potential disadvantage of approach (i) compared to (ii).

### 4. Stop-and-wait and Sliding Window

Nodes A and B are connected by a link with bandwidth 100 Mbps. The delay between A and B is 8 ms. Data packet size is 1000 Bytes, and ACKs have negligible size. Timeout for the Sliding Window problems is  $2 \times \text{RTT}$ .

- a. What is the maximum throughput using stop-and-wait?
- b. What is the throughput using a Sliding Window with  $SWS=RWS=5$ ?
- c. Draw the timeline when the 4<sup>th</sup> ACK is lost.
- d. What is the minimum size of the SWS and RWS that can get the maximum throughput?
- e. Using the SWS and RWS size in (c), what is the throughput when every 100<sup>th</sup> packet is lost (the first send of packet number 100, 200, 300, etc. are lost; resends are not lost)?

## 5. Sliding Window

Suppose that we run the sliding window algorithm with  $SWS = 5$  and  $RWS = 3$ , and no out-of-order arrivals.

- a. Find the smallest value for  $MaxSeqNum$ . You may assume that it suffices to find the smallest  $MaxSeqNum$  such that if  $DATA[MaxSeqNum]$  is in the receive window, then  $DATA[0]$  can no longer arrive.
- b. Give an example showing that  $MaxSeqNum - 1$  is not sufficient.
- c. State a general rule for the minimum  $MaxSeqNum$  in terms of SWS and RWS.

## 6. Token Ring Throughput

Consider a token ring with a data rate of 50 Mbps, a ring latency of 120  $\mu$ sec, and 1000 bit packets.

- a. Assuming only one host wants to transmit and the delayed token release scheme is used, what is the maximum effective throughput rate that can be achieved? What is the efficiency?
- b. Now assume  $N$  hosts want to transmit on the token ring and the token holding time (THT) is 250  $\mu$ sec. What is the token rotation time? What is the maximum effective throughput rate that can be achieved? What is the efficiency?
- c. Under the assumptions of part b, and using the immediate release scheme, what is the throughput rate that can be achieved?